

Thank you for using our company remote controller products. When it is the first time to put in the batteries, please try it first. If it could work well with all of its functions, the product can be used directly without setup. If it could not work well, it should be set with the following methods before controlling your TV. This remote controller would not lose its memory when you change batteries, no need to reset.

Introduction:

RM-L1107+12 is the newest universal LCD/LED TV remote controller, Comprehensive care at different levels need, it can control old or new TV, famous brand or un-famous brand TV, nearly all models for TV. Commonly used functions and menu button all including. Easy setup, conveniently use, it is the best choice for your remote controller losing, damage, replacement, it will bring more convenient for your life.



Battery Installation

In accordance with the "+,-" symbols which is indicated inside the battery cabinet, open the cover and put into two new AAA (AAA) batteries (non-rechargeable), which is shown in the figure.

Battery Description


The remote controller is a low-power consume product. The lifetime of batteries is about 12 months under normal circumstances. If it is improperly used or operated, the lifetime would be shortened.
Please do not put old and new batteries or different types of batteries together.

In case of battery leakage, the batteries must be removed and the battery cabinet should be cleaned before putting into new batteries.

You'd better remove the batteries from the battery cabinet if you intend to stop using the remote controller for a long time.

controller will be in the state of Manually searching for the code.

3, Press the "VOLUME+" button one time, the indicator lamp will flash one time, please



Русский

E.Restore factory Settings
Press "SET" button, then press "0", release the button, the indicator will flash two times, the remote controller restore factory Settings

Methods for setting remote controller:

This remote controller has the following methods for setup, you can choose any of them.

A.Automatically searching code:

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV.



2, Press and hold the "SET" button for about 6 seconds, till the indicator lamp lights, the remote controller will enter automatic search state, please pay attention to your TV, see the volume symbol appears on your TV or not, if yes, please release "SET" button at once, set finished.



3, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the buttons, the remote controller will be in the state of inputting code.



4, Enter the first set of three-digit code in order. When you input each digit, the indicator lamp will flash one time, when you enter all of the three digits, the indicator lamp will turn off, setting to be finished. If the code is more than one set, please use first one at first.



5, Test other function buttons (except: SET, POWER, and VOLUME button) can work well or not, such as "MUTE". If not, repeat steps 2 to 3, until you find the suitable code.



6, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

7, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



8, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

D.Point to Point Brand Searching:

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

2, Press the "SET" button, then press "VOLUME+" button, till the indicator lamp will flash one time, please pay attention to your TV, see the volume symbol appears on your TV or not, if yes, please release "SET" button at once, set to be finished.



3, Press "SET" button, then press "POWER" button, till the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



4, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

5, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.

6, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

B.Manually searching for the code:

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV.



2, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



3, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

C.Automatically searching code:

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV.



2, Press and hold the "SET" button for about 6 seconds, till the indicator lamp lights, the remote controller will enter automatic search state, please pay attention to your TV, see the volume symbol appears on your TV or not, if yes, please release "SET" button at once, set finished.



3, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

4, Press the "SET" button, then press "POWER" button, till the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



5, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

6, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



7, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

E.Restore factory Settings

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV.



2, Press and hold the "SET" button for about 6 seconds, till the indicator lamp lights, the remote controller will enter automatic search state, please pay attention to your TV, see the volume symbol appears on your TV or not, if yes, please release "SET" button at once, set finished.



3, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

4, Press the "SET" button, then press "POWER" button, till the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



5, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

6, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



7, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

F.Manually searching for the code:

1, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV.



2, Press and hold the "SET" button for about 6 seconds, till the indicator lamp lights, the remote controller will enter automatic search state, please pay attention to your TV, see the volume symbol appears on your TV or not, if yes, please release "SET" button at once, set finished.



3, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

4, Press the "SET" button, then press "POWER" button, till the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



5, Turn on your TV set, let your TV set be in the normal state play, and aim the remote controller in the front of the TV. Find out the corresponding brand of your TV on this remotecontrol, for example, SKYWORTHY = "0"

6, Press and hold the corresponding brand button for three seconds, the indicator lamp will flash, when the volume symbol appears on your TV, release button at once, the indicator lamp will turn off, set to be finished.



7, Press "SET" button, then press "POWER" button, till the indicator lamp lights, then release the button, the remote

G.Troubleshooting

1, If the remote controller does not work, please check the batteries, if the batteries are dead, please replace them.

2, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

3, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

4, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

5, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

6, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

7, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

8, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

9, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

10, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

11, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

12, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

13, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.


14, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

15, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

16, If the remote controller does not work after setup, please check the indicator lamp, if the indicator lamp is not working, please replace the indicator lamp.

C.Модели с функцией
автоматического поиска

1, Включите телевизор и направьте на него пульт.



3, Используйте пульт для включения телевизора, когда индикатор не горит, нажмите на него один раз.

4, Проверьте работу других кнопок, кроме кнопки питания.

5, Используйте пульт для включения телевизора, когда индикатор горит, нажмите на него один раз.

6, Повторите шаги 4-5 для всех остальных кнопок.

B. La búsqueda manual del código

1, Encender el televisor, apunte el control remoto hacia televisor.

2, Presione al mismo tiempo el botón SET y POWER, hasta que la luz indicadora se encienda, luego suelte el botón por lo que se convierte en el estado de entrada de código.

3, presione el botón de volumen + una vez y luego suéltelo. ver si el símbolo de volumen aparece en la pantalla de TV, si no se produce tal símbolo, repita el procedimiento.

4, Despues de que el símbolo de volumen aparece, pruebe otro botón de función (excepto el ajuste(SET), POWER, VOLUMEN), si bien el trabajo, pulse el botón de ajuste inmediatamente y la luz de indicación se apagará, lo que significa que la configuración se ha terminado.

D. La búsqueda manual del código

1, Encender el televisor, apunte el control remoto hacia televisor.

2, Presione al mismo tiempo el botón de ajuste(SET) durante unos 6 segundos hasta que la luz indicadora se encienda. Ver si el símbolo de volumen aparece en la pantalla, si es así, suelte el botón SET para detener la búsqueda automática.

3, prueba otro botón de función (excepto el ajuste (SET), POWER, VOLUMEN), si bien el trabajo, pulse el botón de ajuste inmediatamente y la luz de indicación se

4, Despues de que el símbolo de volumen aparece, pruebe otro botón de función (excepto el ajuste(SET), POWER, VOLUMEN), si bien el trabajo, pulse el botón de ajuste inmediatamente y la luz de indicación se

E. La búsqueda automática del códigos.

1, Encender el televisor, apunte el control remoto hacia televisor.

2, Presione y mantenga el botón de ajuste(SET) durante unos 6 segundos hasta que la luz indicadora se encienda. Ver si el símbolo de volumen aparece en la pantalla, si es así, suelte el botón SET para detener la búsqueda automática.

3, prueba otro botón de función (excepto el ajuste (SET), POWER, VOLUMEN), si bien el trabajo, pulse el botón de ajuste inmediatamente y la luz de indicación se

4, Despues de que el símbolo de volumen aparece, pruebe otro botón de función (excepto el ajuste(SET), POWER, VOLUMEN), si bien el trabajo, pulse el botón de ajuste inmediatamente y la luz de indicación se



HUAYU®

RM-L1107+12

HOB331
AKAI
A4001032

HOB353

KM1128

HOB368

S5 S6 S7

S8 S9

LCD-2318

HOD142

HOD142

HOD148

VT-L9A11

HSR553

CYFROWY

POLSAT

HSR585

IPM

PLATFORM

Singer LCD TV

901-7650-

31SG1G

LCD-TV

FU-1

LCT

01

LCT

02

148

148

HOB393

1253

12-17-2011_001

AOC-01

AOC-02

BENQ-01

BENQ-02

BENQ-03

BENQ-04

BENQ-05

VIZIO

NEC

RP-42L1

SANYO

JXPYR

ROLSEN

RL-32L700U

POLYTRON

81f579

SAM_2446

SAM_2443

SAM_2457

lcd tv

AKAI
A3001012

AKAI

CX-507

BBK

EN-31907

CHANGHONG

GH-K-4421A

E-RCU-015

BBK_EN-31907

Benq

china

EcoStar 2

HCH067-

CHANGHONG

GH-K-4421A

Heir 2

HOB477

AKAI CX-507

E-RCU-015

HOB479

AKAI A3001012

HOB484

Akai LTA

-15A15M

HOB489

MESTERY LCD

LED TV NEW

HOBA90

Polar HTR

-D18A

HOB491

Polar 55

LTv6002

Orient

PROTON 2

POLYTRON

EN-31618P

81E878

HOB864

SNOWA

T202-1

HOB455

ELECTRON

T-81100

HOB464

BRAVIS

LED2868 HQ

HOB465

DIGITAL

DLE-4011

HOB46

LUXEON

LED3213 HQ

ORION EP

22

LCD2623

HAIER

HOB493

SUPRA

HOB494

SUPRA

HOB495

ORION

EP-4011

HOB496

HAIER

HOB497

HAIER

HOB498

HAIER

HOB499

HAIER

HOB500

HAIER

HOB501

HAIER

HOB502

HAIER

HOB503

HAIER

HOB504

HAIER

HOB505

HAIER

HOB506

HAIER

HOB507

HAIER

HOB508

HAIER

HOB509

HAIER

HOB510

SHOWMIC

LEA-19V07P

IZUMI

81F579

ORION

OR-LCD2

FUSION

RC21b

SUPRA

RC6w

SUPRA

RC8b

SUPRA

RC10w

SUPRA

RC18b

RC-LEM100

BBK

RC-LEM101

RC-LED100

IZUMI

TL26H211B

JAC

SKY LINE

TRUMAN

union tech

ATLAS HD100

HOB688

ATLS-HD-200S

KK-Y331J

KK-Y331J

HD LED100

GBTY

ONGOV59

XY-B02E

LCD TV PHONAR

PHONAR

LED TV

DAWA MV


iDEA

iDEA

iDEA

iDEA

iDEA

411	412	413	414	415	416	417	418	419	420	421	422	423	424	426	427	428	429	430	431	432	433	434	435	436	437	438	439	440	441			
																																
iDEA	iDEA	iDEA	iDEA	AOC-02	DEX LT-2220	ORION LED2643	Akai SLP-006P	Fusion FLTV 22H11	Fusion FLTV 32H17	FUSION RC15b	Shivaki K77	Shivaki K78	Supra TV-DVD	RC-GK22G1	H-LCD3210	LED321LC	SKYPRIME HD	SUPRA RC21b-1219	ORION LCD	TC1860F1-RS	JH-11370	LED-851	RC-D3	YC-53	STV-22LEDS	LED-EH4720BF	DNS M28AM8	051D RED	33585			
442	442	442	442	443	444	445	446	449	450	451	452	453	454	516	520	528	531	540	542	543	544	545	546	547	548	549	540	550	551	533		
																																
576	577	578	579	580	581	582	583	584	585																							
																																
VESTEL LCD T1396	VESTEL LCD	HAIER HTR-A10	EN3V39H	VESTEL LCD T1560	MICROMAX	RECONNECT	YASIN	HISENSE	SANSUI																							